

904 Serial, w/LCD, 6 ft cable, USB or Wireless USB

(SKU#904)



Product Highlights

Description:	Serial	X
	USB	
	Wireless	
	Back-lit LCD	X
	Magnetic Card Reader	
	Bar Code Reader	
	6 foot cable	X
	25 foot cable	

The Genovation Mini-Terminal, available in 12 key configuration, is a macro-programmable LCD serial terminal that also includes a programmable buzzer. The Mini-Terminal supports simple and complex re-programmable key macros as well as re-programmable system configuration through the RS232 serial port with a wide variety of baud rates and word formats.

- 12-Key Tactile Membrane Keypad (Sealed)
- 1x16 Super-Twist back-lit LCD display (Sealed)
- Fully-Programmable Serial Settings
- Fully-Programmable Key Table
- RS232C Compliant (Half-Duplex)
- Serial Cable (6' or 2 Meters)
- Internal Buzzer/Alarm (Audible Key Beeper)
- Internal "Flash" memory holds Key data and Settings.
- Includes Genovation re-programming software "MacroMaster232" for easy customization & setup
- Operates in standard terminal or line-edit (pin-pad)

mode

Type : Tactile Membrane, 12-key Terminal
Interface : Standard RS232C Serial
Dimension : 4.5" x 3.75" x 2"
Weight : 0.50 lb

OS Requirements

OS Supported: Windows 95 / 98, NT 4.0, 2000, ME, XP
Standard RS-232 works on any OS

Specifications

- Connects to RS232C serial port (DB-9)
- Two levels; 100 bytes per key per level programmability
- 12-key Tactile Membrane (20,000,000+ operations)
- Keypad size is 6" x 3.75" x 2"
- Temperature range is 0 to 60 deg C (32 to 140 deg F)
- Weight of keypad alone is 0.50 lb
- 1x16 Super-Twist "STN" type back-lit LCD
- 5v DC regulated wall adaptor included
- Complies with FCC